

# IYPT 2011 PROBLEM 13: LIGHT BULB

**Katja Kustura**

University of Zagreb, Croatia

## Introduction

Determining efficiency of a light bulb is a very useful task, since light bulb is a very present and widely used object in everyday life. This was our task in this year's IYPT problem – the goal was to determine the ratio between the thermal energy and the light energy emitted from a small electric bulb depending on the voltage applied to the bulb. Our first and main plan was to distinguish useful part of emitted energy (light) from the energy losses (heat).

We approached this problem in two different ways. First, calorimetric method was used to experimentally separate light and thermal energy and to determine the ratio. Besides this method, theoretical method was proposed and developed, by using Planck's law of radiation and approximating the light bulb as a grey body.

## The light bulb

The light bulb filament is a resistor. Electrical current causes heating. When heated to the temperatures high enough, the filament emits light. The law of conservation of energy for a light bulb is: electrical energy → thermal energy + light. The energy is transferred in three ways:




Figure 1. Transfer of energy

conduction, convection and radiation (fig.1) [1].

Conduction is heat transfer by direct contact (wires, glass).

Convection is heat transfer by gases, caused by buoyancy (warmer gas is lighter and thus moves upwards, transferring the energy). By conduction and convection, the electrical energy is converted to thermal energy. Since the main purpose of a light bulb is producing light, conduction and convection are the causes of energy loss. The third

way of energy transfer is radiation. All bodies with temperature  $T > 0K$  emit continuous electromagnetic spectrum. They radiate waves of all wavelengths, which means ultraviolet, visible, infrared, microwaves... Planck's law of radiation explains the radiation and gives a connection between intensity of emitted light and the wavelengths, for a given temperature (fig.2). On higher





Figure 2. Black body radiation for 3 different temperatures

temperatures, the total intensity is higher.

A little part of the spectrum (390 – 750 nm) is visible. Human eye can only detect light at higher temperatures (because of the greater intensity). This is why the light bulb is heated in the first place – for the light to be detected.

We defined efficiency of a light bulb as a ratio between visible energy (useful) and electrical energy (total)  $\rightarrow \eta = \frac{P_{\text{visible}}}{UI}$ .

### Calorimetry method



**Figure 3. Absorbance factor of water [3]**

The only flaw of this filter is that it does not absorb the radiation 300 – 900 nm. This interval is a little greater than the interval of visible light, so a little amount of infrared and ultraviolet radiation is not absorbed, which caused small error in experiment. But, the results were still valid since they were comparable with the already obtained values (from the literature).

The light bulb was put in the glass vessel with water and turned on. Due to water absorbance factor for each wavelength, only visible light passed through the vessel (fig.4a). The rest of the spectrum stayed in the vessel and heated the water. The water temperature was measured with the precision of  $10^{-4}$ K. Graph showing the change of temperature in time was obtained (graph 1). The measurement was repeated, but this time *carbon* was put inside the water, which made it black, not transparent for visible light (fig.4b). All the energy produced by the light bulb stayed in the water and heated it.




**Figure 4a. Light passing through**



**Figure 4b. Light not passing through**

We obtained another temperature-time graph. By comparing heating rates we measured the ratio between visible and total energy (efficiency of a light bulb). Power heating the water in the first case:  $P_1 = UI - P_{300-900nm} = C \left( \frac{dT}{dt} \right)_1 = Ca$ . Power heating the water in the second case:  $P_2 = UI = C \left( \frac{dT}{dt} \right)_2 = Ca'$ . Here  $C$  is heat capacity of the system, and  $a, a'$  are heating rates – slopes in  $T-t$  diagrams. Efficiency of a light bulb is  $\eta = \frac{P_{300-900nm}}{UI} = 1 - \frac{a}{a'}$ .



- phase 2: light bulb turned on  
 - phases 1 & 3: light bulb turned off (small temperature change!)

- determining  $dT/dt$ :

$$a = a_2 - \frac{a_1 + a_3}{2}$$

**Graph 1. Temperature-time dependence**


### Black body method

Light bulb was considered a grey body. It behaves as a non ideal black body – it radiates electromagnetic spectrum with the intensity dependant on temperature, but with emissivity factor  $\epsilon$  (constant over all wavelengths and temperatures). Stefan-Boltzman law:  $\sigma S \epsilon T^4 = P_{\text{visible}} + P_{\text{IR}}$  where  $S$  is the surface of the body, and  $T$  its temperature (here we neglected all the other parts of the spectrum, ultraviolet, microwaves... because these energies are much smaller than in infrared and visible spectrum). If we relate this law to law of conservation of energy, we can derive the ratio


$$\frac{P_{\text{IR}}}{P_{\text{V}}} \text{ as a function of temperature, i.e. } \frac{P_{\text{IR}}}{P_{\text{V}}} = f(T). \text{ The final formula is } \eta = \frac{\sigma S \epsilon T^4}{UI \left( \frac{P_{\text{IR}}}{P_{\text{V}}} + 1 \right)}.$$

Thus, for calculating the efficiency we need to know the temperature of a filament as a function of voltage, value of  $\sigma S \epsilon$  constant and ratio of powers  $P_{\text{IR}}/P_{\text{V}}$  as a function of voltage.

From the literature, we knew the connection between filament resistivity and temperature [4]. Measuring  $U-I$  characteristics of a bulb, we determined resistance (in dependence on voltage). By knowing the resistance at the room temperature, with little transformations we got final graph showing the dependence of temperature of a filament on a voltage applied (graph 2).



**Graph 2. Temperature – voltage dependence**



**Graph 3. UI/T<sup>4</sup> – temperature dependence**

We rewrite the law of conservation of energy:  $UI = \alpha(T - T_0) + \sigma S \varepsilon (T^4 - T_0^4)$ , where the first member is due to conduction and convection, and the second is from radiation. We can write this as  $\frac{UI}{T^4 - T_0^4} = \frac{\alpha(T - T_0)}{T^4 - T_0^4} + \sigma S \varepsilon$ . It is obvious that for  $T \gg T_0$  value  $UI/T$  equals  $\sigma S \varepsilon$ . From this graph the constant  $\sigma S \varepsilon$  was determined (graph 3) [5].

The program was created in C programming language to determine the ratio  $P_{IR}/P_v$  as a function of temperature. In this program the only input was the temperature. The program then plotted Planck's curve and numerically integrated the visible part of the spectrum (the limits were 300 – 900 nm) and then the ratio of visible and total energy was calculated. This result was compared with the result obtained in the calorimetry method.


### Final results

By calorimetry method, efficiency of light bulb (ratio  $P_{IR}/P_v$ ) was determined for 4 different voltages. Using black body method, we got theoretical predictions for a light bulb for a greater interval of voltages. The results were put on the same graph to compare the methods. In the experimental setup, light of wavelengths 300 – 900 nm was considered visible light (because water did not absorb that part of the spectrum and we were able to separate it from the rest of the spectrum). In our theoretical calculation, limits were the same, because the goal was to compare these two methods for their validation.


From the graph it can be seen that both methods have similar results (graph 4). Theoretical prediction for 300 – 900 nm limits matches the experimental results. Although in our limits we took 300 – 900 nm instead of a smaller interval of visible part of the spectrum, from this results we see that the theory is valid, which means that it can be used to determine the real efficiency of a light bulb (limits 390 -750 nm).

Finally, since the initial task was to determine the ratio between the thermal energy and the light energy, that is what we did in our last graph (graph 5). The

efficiency was defined as  $\eta = \frac{P_V}{UI} = \frac{P_V}{P_V + P_{IR}}$ . Transformations of the expression lead to formula  $\frac{P_{IR}}{P_V} = \frac{1}{\eta} - 1$ .



**Graph 4. Efficiency – voltage dependence**



**Graph 5. Ratio  $P_{IR}/P_V$  – voltage dependence (real light limits)**

## Conclusion

In this paper the efficiency of a light bulb was studied and determined. Two methods were proposed. We experimentally determined efficiency using calorimetry method. In this experiment we assumed that the visible part of the electromagnetic spectrum was 300 – 900 nm, because these are the limits in which water does not absorb the radiation. This property of water was used to separate the light energy from the thermal energy. The results were then compared with the expected results that we got using our theoretical method. In this method we created a program that calculated  $P_{IR}/P_V$  ratio for each temperature, in wanted limits. For limits 300 – 900 nm, the theoretical results were compared with our experimental values. Two approaches showed a good agreement. Once we confirmed our theoretical method, we changed the limits in the program to 390 – 750 nm and obtained the final results and the dependance of the ratio of the thermal and visible energy on voltage applied to the bulb.

## References

- [1] Martchenko, I. (2011). "Preparation to the Young Physicists' Tournaments' 2011". ([http://ilyam.org/Draft\\_2011\\_IYPT\\_Reference\\_kit\\_IM.pdf](http://ilyam.org/Draft_2011_IYPT_Reference_kit_IM.pdf))
- [2] Hale, G.M., and Querry, M.R. (1973). "Optical constants of water in the 200 nm to 200  $\mu$ m wavelength region". Applied Optics, Vol. 12, Issue 3, pp. 555-563.
- [3] Segelstein, D. (1981). "The Complex Refractive Index of Water". M.S.Thesis, University of Missouri, Kansas City ([http://people.seas.harvard.edu/~jones/es151/gallery/images/absorp\\_water.html](http://people.seas.harvard.edu/~jones/es151/gallery/images/absorp_water.html))
- [4] Jones, H.A., (1926). "A temperature scale for tungsten". Physical review, Vol. 28, pp. 202-207.
- [5] de Izarra, C., and Gitton, J.M. (2010). "Calibration and temperature profile of a tungsten filament lamp". European Journal of Physics, Vol. 31, Issue 4, pp. 933.